

# Denver SHC-150






- Digital indoor IP dome camera with IR led's for night use
- Pair with your home Wi-fi and use the camera online (WEP/WPA/WPA2)
- 1mpixel sensor - HD resolution 720P - 1280x720@12fps)
- Pan 355°/Tilt 90° - motorized
- TUYA smart home compatible (uses DENVER SMART HOME app)
- Built-in speaker & microphone
- IR distance up to 10 meters
- Motion detection (records 20-30 seconds minute per motion) + manual access (Motion detection up to 10 meters, a bit lower at night)
- MicroSD card slot - up to 128gb (not incl.)

If you get an error message that the camera has already been paired to another account, please do as follows:

1. Connect camera to power
2. Push and hold the small reset button and KEEP on holding, even though the camera says it is reset and will reboot.. Hold it for at least 10-15 seconds and then let go.

Now you should be able to pair it, as it is completely reset and has lost it's old pairing.



-  Highlights  
Smart Wi-Fi camera, 1mpixel CMOS sensor, Tuya compatible
-  Power  
230V~50Hz AC/DC adaptor
-  Camera  
1Mpixel CMOS sensor
-  Storage  
Needs MicroSD card (not included)
-  Connections  
DC input, MicroSD card slot

## Shipping information

Unit size: 7.00(w) x 8.50(d) x 10.50(h) cm  
Gross weight: 0.341  
Giftbox size: 14.00(w) x 11.70(d) x 8.80(h) cm  
8 Pcs./export carton  
23160 Pcs./20' container  
61410 Pcs./40' HQ container  
Barcode: 5706751047916